

## HSA-320/1+1 M

- Surge arresters type T2+T3 ensure the equipotential bonding and reduce switching, induced and residual overvoltage in LV power supply systems.
- The products consist of varistors with big discharge ability.
- Configurations 1+1 and 3+1 are additionally combined with a gas discharge tube which ensures zero leakage current through the PE conductor.
- Installed at the boundaries of LPZ 1 LPZ 3 into subsidiary switchboards and control panels.
- If the product contains two PE (or PEN) terminals, it must not be used as a PE (PEN) bridge.
- **M** indication specifies a type of construction with removable module.
- **S** indication specifies a version with remote monitoring.

Туре		HSA-320/1+1 M
Test class according to EN 61643-11:2012 (IEC 61643-11:2011)		T2, T3
System		TN-S, TT
Number of poles		2
Rated operating AC voltage	$U_N$	230 V
Maximum continuous operating voltage AC	U <sub>c</sub>	320 V
Maximum discharge current (8/20)	I <sub>max</sub>	50 kA
Nominal discharge current for class II test (8/20)	I <sub>n</sub>	20 kA
Open circuit voltage of the combination wave generator	U <sub>oc</sub>	6 kV
Total discharge current (8/20) L+N->PE	I <sub>Total</sub>	50 kA
Voltage protection level at I <sub>n</sub> (L/N)	$U_p$	< 1.4 kV
Voltage protection level at I <sub>n</sub> (L/PE)	$U_p$	< 1.5 kV
Voltage protection level at I <sub>n</sub> (N/PE)	$U_p$	< 1.4 kV
Voltage protection level at U <sub>oc</sub> (L/N)	$U_p$	< 0.95 kV
Impulse discharge current for class I test (10/350) N/PE	I <sub>imp</sub>	20 kA
Temporary overvoltage test (TOV) for $t_T = 5 \text{ s (L/N)}$	U <sub>T</sub>	337 V
Temporary overvoltage test (TOV) for $t_T = 120 \text{ min (L/N)}$	U <sub>T</sub>	440 V
Temporary overvoltage test (TOV) for $t_T = 0.2 \text{ s (N/PE)}$	U <sub>T</sub>	1 200 V
Response time (L/N)	t <sub>A</sub>	< 25 ns
Response time (N/PE)	t <sub>A</sub>	< 100 ns
Maximal back-up fuse		160 A gL/gG
Residual current	I <sub>PE</sub>	≤ 5 μ <b>A</b>
Short-circuit current rating at maximum back-up fuse	I <sub>SCCR</sub>	60 kA <sub>rms</sub>
Follow current interrupt rating (N/PE)	I <sub>fi</sub>	0.1 kA <sub>rms</sub>
Lightning protection zone		LPZ 1-2, LPZ 2-3
Housing material		Polyamid PA6, UL94 V-0
Degree of protection		IP20
Operating temperature	Э	-40 ÷ 70 °C
Humidity range	RH	5 ÷ 95 %



Туре		HSA-320/1+1 M
Minimum cross-section of connected Cu conductors accord. to HD 60364-5-53:2022 (doesn't apply to "V" connection) for T2	S	2.5 mm <sup>2</sup> (L, N) 6 mm <sup>2</sup> (PE, PEN)
Clamp fastening range (solid conductor)		1.5 ÷ 25 mm <sup>2</sup>
Clamp fastening range (stranded conductor)		$1.5 \div 16 \text{ mm}^2$
Tightening moment		3 Nm
Installation		On DIN rail 35 mm
Modular width		2 TE
Operating position		Any
Product placement environment		Internal
Signalling at the device		Optic
Importance of local signaling		OK – clear target FAULT – red target
Remote signalling		No
Modular design		Yes
Article number of spare module		27 192
Lifetime		> 100 000 h
Designed according to standards		
Requirements and test methods for SPDs connected to low-voltage power systems		IEC 61643-11:2011
Safety of Flammability of Plastic Materials		UL 94
Application standards		
Protection against lightning		IEC 62305:2010
Selection and erection of electrical equipment – Switchgear and controlgear		HD 60364-5-53:2022
Selection and application principles for SPDs connected to low-voltage power systems		CLC/TS 61643-12:2009
Ordering, packaging and additional data		
Mass	m	230 g
Mass (including the packaging)	m	244 g
Packaging dimensions (H x W x D)		45 x 102 x 74 mm
Packaging value	V	0.34 dm <sup>3</sup>
ETIM group		EG000021
ETIM class		EC000941
Customs tariff no.		85363010
EAN code		8590681116456
Art. number		27 520




**The link in the QR code** leads to the online presentation of the **HSA-320/1+1 M**. There, in addition to the always up-to-date data sheet, you will also find all diagrams and drawings, declarations of conformity, or 2D or 3D models and other necessary materials. For more information, visit **www.hakel.com** 





## Application wiring diagram (installation)



## Internal diagram

